

Arteor™ dimmers

round version



Support frame and plate selection charts **p. 88-95**

Mechanisms supplied with rocker plates, to be equipped with support frames (p. 77) and plates (p. 84-91)
100/240 VA - 50/60 Hz

Resistive/inductive loads touch dimmers

Pack	Cat.Nos	
1	5 743 05	Without neutral, 2-wire
1	5 743 55	Push-button dimmer - 600 W To be installed alone in a 3 module box with a 3-module support frame and a 2-module plate ○ White - 2 modules ● Magnesium - 2 modules



Pack	Cat.Nos	
1	5 722 40	Leading edge dimmers Without neutral, 2-wire
1	5 727 40	Rotary dimmer - 1000 W To be installed alone in a 3 module box with a 3-module support frame and a 2-module plate Not CE compliant ○ White - 2 modules ● Magnesium - 2 modules



Pack	Cat.Nos	
1	5 743 07	Trailing/leading edge dimmers Push-button dimmer - 2 x 400 W With Magnesium circle for control Supplied with support frame ○ White - 2 modules ● Black - 2 modules
1	5 743 57	
1	5 743 06	Push-button dimmer - 600 W To be installed alone in a 3 module box with a 3-module support frame and a 2-module plate ○ White - 2 modules ● Magnesium - 2 modules
1	5 743 56	



Pack	Cat.Nos	
1	5 743 08	Universal dimmers Push-button dimmer 300 W With neutral, 3-wire Can be used with compact fluorescent lamps With Magnesium circle for control ○ White - 2 modules ● Black - 2 modules
1	5 743 58	



Pack	Cat.Nos	
1	5 743 09	Dimmers 0-10 V Push-button dimmer For ballasts 0-10 V With Magnesium circle for control ○ White - 2 modules ● Black - 2 modules
1	5 743 59	



Arteor™ load selection charts

Load selection charts

	Cat.Nos	Universal							
		Leading edge				Trailing edge			
		Incandescent lamp		Halogen lamp		ELV halogen with ferromagnetic transformer		ELV halogen with electronic transformer	
		110 V	230 V	110 V	230 V	110 V	230 V	110 V	230 V
Micropush switches	5 740 04/54 5 743 04/54	200 W	400 W	200 W	400 W	200 VA	400 VA	200 VA	400 VA
	5 740 02/52 5 743 02/52	500 W	1000 W	500 W	1000 W	250 VA	500 VA	250 VA	500 VA
	5 740 03/53 5 743 03/53	2 x 500 W	2 x 1000 W	2 x 500 W	2 x 1000 W	2 x 250 VA	2 x 500 VA	2 x 250 VA	2 x 500 VA
	5 740 00/50 5 743 00/50	3 x 500 W	3 x 1000 W	3 x 500 W	3 x 1000 W	3 x 250 VA	3 x 500 VA	3 x 250 VA	3 x 500 VA
	5 740 01/51 5 743 01/51	2 x 200 W	2 x 400 W	2 x 200 W	2 x 400 W	2 x 200 VA	2 x 400 VA	2 x 200 VA	2 x 400 VA
Sensitive switches	5 720 51 5 734 55 5 725 51 5 736 55	500 W	1000 W	500 W	1000 W	250 VA	500 VA	250 VA	500 VA
Dimmers	5 740 06/56 5 743 06/56	300 W	600 W	300 W	600 W	225 VA	450 VA	300 VA	600 VA
	5 735 01 5 737 01 5 722 40 5 727 40	500 W	1000 W	500 W	1000 W	500 VA	1000 VA	300 VA	600 VA
	5 722 11 5 727 11 5 743 05/55	300 W	600 W	300 W	600 W	300 VA	600 VA		
	5 740 08/58 5 743 08/58	150 W	300 W	150 W	300 W	150 VA	300 VA	150 VA	300 VA
	5 740 07/57 5 743 07/57	2 x 200 W	2 x 400 W	2 x 200 W	2 x 400 W	2 x 200 VA	2 x 400 VA	2 x 200 VA	2 x 400 VA
	5 722 41 5 727 41	500 W	1000 W	500 W	1000 W	500 VA	1000 VA	500 VA	1000 VA
	5 740 10/60	1100 W	2200 W	1100 W	2200 W	1100 VA	2200 VA	1100 VA	2200 VA

	Cat.Nos	Universal					
		Fluorescent tube		Compact fluorescent lamp		LED	
		110 V	230 V	110 V	230 V	110 V	230 V
Micropush switches	5 740 02/52 5 743 02/52	250 VA	500 VA	250 VA	500 VA	250 VA	500 VA
	5 740 03/53 5 743 03/53	2 x 250 VA	2 x 500 VA	2 x 250 VA	2 x 500 VA	2 x 250 VA	2 x 500 VA
	5 740 00/50 5 743 00/50	3 x 250 VA	3 x 500 VA	3 x 250 VA	3 x 500 VA	3 x 250 VA	3 x 500 VA
Sensitive switches	5 720 51 5 734 55 5 725 51 5 736 55	250 VA	500 VA	250 VA	500 VA	250 VA	500 VA
Dimmers	5 740 08/58 5 743 08/58	80 VA	160 VA	80 VA	160 VA		

	Cat.Nos	Ballasts 0-10 V		Ballasts DALI		Reducer motor for shutters	
		110 V	230 V	110 V	230 V	110 V	230 V
Micropush switches	5 740 02/52 5 743 02/52					50 VA	100 VA
	5 740 03/53 5 743 03/53					2 x 50 VA	2 x 100 VA
	5 740 00/50 5 743 00/50					3 x 50 VA	3 x 100 VA
Sensitive switches	5 720 51 5 734 55 5 725 51 5 736 55					50 VA	100 VA
Dimmers	5 722 10 5 727 10 5 743 09/59	300 VA 40 mA	600 VA 40 mA				
	5 740 10/60	1100 VA 50 mA	2200 VA 50 mA	60 ballast	60 ballast		