# AMG INDUSTRIAL HARDENED Mini MEDIA CONVERTERS



# Ruggedised Industrial Ethernet Solutions

AMG's Mini media converters provide a 100Mbps or Gigabit Ethernet uplink across fibre via the SFP port.















[ AMG9HMEC-1G-1S ]

#### / OVERVIEW

Housed in a mini chassis, these DIN rail mountable devices are ideally suited for connecting field based equipment such as IP CCTV cameras and industrial controllers to Ethernet networks over long distances using all types of fibre. Fibre connectivity is determined by separate SFP device selection, providing application and site flexibility.

SFPs and PSUs need to be ordered seperately.

#### / FEATURES

- Mini size ideal for confined spaces, including camera poles and roadside cabinets
- -40°C to 75°C temperature maintains performance in extreme conditions
- Non-programmable no need for any user configuration or computer setup
- DIN rail mountable quick to install and remove for maintenance
- Gigabit or 100M SFP port supports single and multimode, single or dual fibre options up to 120Km
- Gigabit or 10/100M Ethernet copper ports high bandwidth support
- Auto MDI or MDI-X config eliminates the need for crossover cables
- Auto-Negotiation (802.3u) automatically determines the best connection speed
- Automatic Link Restoration restores operation when recovering from a temporary fault



## Specifications.

#### Standards.

IEEE802.3 10BaseT IEEE802.3u 100BaseTX IEEE802.3ab 1000BaseT 1000BaseSX/LX IEEE802.3z

#### Interface.

**LED Indicators** 

Power: ON = Link; Flashing = Activity ON = Link; Flashing = Activity Fiber Link/Act: Copper Link/Act: ON = Link; Flashing = Activity

**RJ45 Ports** 1x 10/100Tx or

> 1x 10/100/1000TX RJ45 with Auto MDI/MDI-X

SFP Slot 1x 100M or 1x 1000M SFP

1x 2 pin removable Power terminal block

#### Power.

Input: 12-24V<sub>DC</sub> (Non-PoE)

48-56Vpc (PoE)

Consumption 3W Max

Protection Reverse Polarity, **Overload Current** 

#### Mechanical.

Anodised Aluminium Casing **Dimensions**  $55 \times 55 \times 26 \text{ mm}$ 

**IP** Rating IP30

Installation Stand-alone or DIN-Rail

Weight 0.2kg

#### Packaging.

Shipping Weight 0.52kg

**Dimensions** 250 × 200 × 65 mm

#### Environmental.

-40°C to 75°C Operating Temp. -40°C to 85°C Storage Temp.

Humidity 5% to 90% (non-condensing) Compliances Reach, RoHS and WEEE

MTBF (Hours)\*

Without power adaptor 310,000 With power adaptor 310,000

#### Regulatory.

**Electrical Safety** CE/EN60950-1 **Immunity** EN55022 **Emissions** EN61000-3-2

Environmental

Cold: EN 60068-2-1

Test Ab/Ad to -40°C

Hot: EN 60068-2-2


Test Bb/Bd to +75°C EN 60068-2-14 Test Nb

Change in temp:


Humidity: EN 60068-2-56

Test Cb +55°C/95%RH Condensation: EN 60068-2-30 Test Db

RH30°C, 90-100% RH











### Part Numbers.

AMG9HMEC-1F-1S	$1\times10/100$ Base Ethernet, $1\times100$ Base SFP, -40°C to +75°C. 15-25 $V_{_{\rm DC}}$ Power Input
AMG9HMEC-1G-1S	1 × 10/100/1000 Base Ethernet, 1 × 1000 Base SFP, -40°C to +75°C. 15-25 V $_{\rm DC}$ Power Input
AMG9HMEC-1FH-1S-P30	$1 \times 10/100$ Base Ethernet, PoE(at), $1 \times 100$ Base SFP, -40°C to +75°C. 48-56 $V_{DC}$ Power Input
AMG9HMEC-1GH-1S-P30	$1\times10/100/1000$ Base Ethernet, PoE(at), $1\times1000$ Base SFP, -40°C to +75°C. 48-56 $V_{\rm DC}$ Power Input
AMG9HMEC-1F-1SL	$1\times10/100$ Base Ethernet, $1\times100$ Base SFP, -40°C to +75°C. 15-25 $V_{_{\rm DC}}$ Power Input + LLF
AMG9HMEC-1G-1SL	1 × 10/100/1000 Base Ethernet, 1 × 1000 Base SFP, -40°C to +75°C. 15-25 V $_{\rm DC}$ Power Input + LLF
AMG9HMEC-1FH-1SL-P30	$1 \times 10/100$ Base Ethernet, PoE(at), $1 \times 100$ Base SFP, -40°C to +75°C. 48-56 $V_{DC}$ Power Input + LLF
AMG9HMEC-1GH-1SL-P30	1 × 10/100/1000Base Ethernet, PoE(at), 1 × 1000Base SFP, -40°C to +75°C. 48-56V <sub>DC</sub> Power Input + LLF

## Recommended PSUs.

AMG2001 Standalone PSU, 15V DC, 15W DIN-Rail mounting PSU, 15V DC, 24W DIN-Rail mounting PSU, 48-56VDC, 30W

### Notes.

Optional Accessories: SFP modules - Optical/Copper see separate list, need to be ordered separately

LLF: Link Loss Forwarding - Fibre and Copper Link failure recognition and forwarding to the remote end media converter

