

## RX 212 & TX 212

- ✦ Infrared receiver support MLP1 / MLP2 Protocol
- ✦ Distance of IR remote control is 10 meter
- ✦ IR remote control equips PCM to avoid noise of fluorescent light
- ✦ Easy to install and control
- ✦ Small volume of receiver and save your space



### Specifications

#### ✦ Infrared Remote Controller / Infrared Receiver

| Model                           | TX212                             | RX212                           |
|---------------------------------|-----------------------------------|---------------------------------|
| Power Supply                    | DC 3.0V [ AAA(UM-4) battery x 2 ] | DC 12V $\pm$ 10%                |
| Power Consumption               | 120 mW                            | 1W                              |
| Ambient Operation Temperature   | 0°C ~ + 40°C ( 32°F ~ 104°F )     | -10°C ~ + 50°C ( 14°F ~ 122°F ) |
| Operating Humidity              | 0% ~ 90%                          |                                 |
| Infrared Beam Spread            | 30°                               |                                 |
| Infrared Radiant Distance       | 10 M                              |                                 |
| Infrared Frequency              | 38 KHz                            |                                 |
| Communication Control Interface | -                                 | RS-485                          |
| Dimensions                      | 50mm (W) x 22mm (H) x 175mm (D)   | 72mm (W) x 28mm (H) x 100mm (D) |
| Weight                          | 80g ( excluded battery )          | 60g                             |